


107 OR

Stopfen mit O-Ring

Parallel male plug with o-ring

Tappo maschio cilindrico con O-Ring




ITV	G	ØB	H	L	Ø
30150	M5	8	4,5	7,5	2,5
30151	M7	11	6	9	4
30152	G1/8	14	6	9,5	5
30153	G1/4	17	8	11,5	6
30154	G3/8	20	9	12,5	8
30155	G1/2	26	11	14	10

107 OR FKM

Stopfen mit O-Ring

Parallel male plug with O-Ring FKM

Tappo maschio cilindrico con O-Ring FKM




ITV	G	ØB	H	L	Ø
V30150	M5	8	4,5	7,5	2,5
V30151	M7	11	6	9	4
V30152	G1/8	14	6	9,5	5
V30153	G1/4	17	8	11,5	6
V30154	G3/8	20	9	12,5	8
V30155	G1/2	26	11	14,5	10

108

Kappe

Female plug

Tappo femmina




ITV	G	H	L	Ø
30302	G1/8	8	11,5	14
30303	G1/4	11	15	17
30304	G3/8	12	15,5	20
30305	G1/2	14	20	24

109

Winkelstück

Female elbow

Gomito F.F.



ITV	G	H	L	Ø
50101	M5	5	11	9
50102	G1/8	8	21	10
50103	G1/4	11	25,5	13
50104	G3/8	11,5	28	17
50105	G1/2	14	33,5	21
50106	G3/4	16,5	36,5	25
50107	G1	19	45	30